

Tech Company

Zen4 Software Configuration Guide

Tech Company Systems, Inc. Legal Notice

Copyright © 2005, 2006 Tech Company Systems, Inc. All rights reserved.

Tech Company Systems, Inc.

11 Lane, Suite 222

Huntsville, AL 11222

Phone: 555-12-1212

www.TechCompany.com

Disclaimer

The information contained in this publication is subject to change without notice. Tech Company Systems, Inc. makes no warranty of any kind with regard to this manual, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose. Tech Company Systems, Inc. shall not be liable for errors contained herein or for incidental or consequential damages in connection with the furnishing, performance, or use of this manual.

Trademarks

The Tech Company logo, Tech Company, Z-Series, Z-Visor, and all other Tech Company Systems, Inc. product names and service marks are trademarks of Tech Company Systems, Inc.

AMD Opteron is a registered trademark of Advanced Micro Devices. Linux is a registered trademark of Linus Torvalds. RED HAT is a registered trademark of Red Hat, Inc. SUSE is a trademark of Novell. VMware® is a registered trademark of VMware, Inc. Microsoft and Windows are registered trademarks of Microsoft Corporation. IBM and Tivoli are registered trademarks of IBM Corporation.

Other product names mentioned herein may be trademarks or registered trademarks of their respective companies.

Printed in USA.

Contents

Chapter 1 Zen4 System and Hardware Overview	8
--	----------

Tech Company Zen4 System and Architectural Overview	9
Abstract	9
Tech Company Zen4 System and Architectural Overview	9
Fabric Computing	10
Abstract	10
Fabric Computing	10
Functional Overview and Features	11
Abstract	11
Functional Overview and Features	11
Integrated Computing and Networking	12
Abstract	12
Integrated Computing and Networking	12
Resource Sharing Across Switch Fabric	13
Abstract	13
Resource Sharing Across Switch Fabric	13
Switch	14
Abstract	14
Switch	14
Network Interfaces	15
Abstract	15
Network Interfaces	15
Virtual I/O Interfaces	16
Abstract	16
Virtual I/O Interfaces	16

Flexible Provisioning	17
Abstract	17
Flexible Provisioning	17
Technical Overview	18
Abstract	18
Technical Overview	18
Processors, Memory, and Partitioning	20
Abstract	20
Processors, Memory, and Partitioning	20
System Management	22
Abstract	22
System Management	22
System I/O Fabric	23
Abstract	23
System I/O Fabric	23
Boot Support	24
Abstract	24
Boot Support	24
Backplane	25
Abstract	25
Backplane	25
Internal Hard Drive	26
Abstract	26
Internal Hard Drive	26

System Battery/System Time	27
Abstract	27
System Battery/System Time	27
Software Components	28
Abstract	28
Software Components	28
Typical System Installation	29
Abstract	29
Typical System Installation	29
Zen4 Hardware Overview	30
Abstract	30
Zen4 Hardware Overview	30
Processor and Memory Zen4 Subsystems Modules	32
Abstract	32
Processor and Memory Zen4 Subsystems Module	32
Z-Series System Module (ZSM)	33
Abstract	33
Z-Series System Module (ZSM)	33
Ethernet Network Module	34
Abstract	34
Ethernet Network Module	34
Fibre Channel Modules	35
Abstract	35
Fibre Channel Modules	35

Application Service Module	36
Abstract	36
Application Service Module	36
Hot-Plugged and Controlled Hot Removal Capability	37
Abstract	37
Hot-Plugged and Controlled Hot Removal Capability	37
High Availability	38
Abstract	38
High Availability	38
Virtual I/O Controller (VIOC) and Virtualization Cap-	
abilities	39
Abstract	39
Virtual I/O Controller (VIOC) and Virtualization Cap-	
abilities	39
Virtual Network Interface Controllers	40
Abstract	40
Virtual Network Interface Controllers	40
Virtual Storage Interfaces	41
Abstract	41
Virtual Storage Interfaces	41
Partitioning and Virtualizing Resources	42
Abstract	42
Partitioning and Virtualizing Resources	42
Data Flow in the Zen4 System	43

Abstract	43
Data Flow in the Zen4 System	43
Appendix A Product Support	44
Warranty	45
Abstract	45
Warranty	45
Verify Warranty Status	46
Abstract	46
Verify Warranty Status	46
How to Verify Warranty Status	46
Service Features and Levels	47
Abstract	47
Service Features and Levels	47
Contacting Customer Support	48
Abstract	48
Contacting Customer Support	48
Return Materials Authorization (RMA) Procedure	49
Abstract	49
Return Materials Authorization (RMA) Procedure	49
Return a Product or Component	50
Abstract	50
Return a Product or Component	50
Labeling Requirements for Return Packages	50
Steps to Return a Product or Component	50

Result	51
Ordering Replacement Parts or Spares	52
Abstract	52
Ordering Replacement Parts or Spares	52
Glossary	53
Index	54

Chapter 1 Zen4 System and Hardware Overview

This chapter introduces the Tech Company Zen4 server and describes its relationship to advanced data center computing. It also gives an overview of important network concepts in the Zen4 system and provides a brief overview of the Zen4 hardware components.

This chapter includes the following sections:

- Tech Company Zen4 System and Architectural Overview
- Technical Overview
- Typical System Installation
- Zen4 Hardware Overview
- Virtual I/O Controller (VIOC) and Virtualization
- Partitioning and Virtualizing Resources
- Data Flow in the Zen4 System

Tech Company Zen4 System and Architectural Overview

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Tech Company Zen4 System and Architectural Overview

The Tech Company Zen4 system integrates highly redundant multiprocessing servers and networking technology in a modular design, which provides efficient use of space and simplifies management tasks. The Zen4 system provides improved data center performance by integrating resources and sharing key components to provide high density processing and Layer 2 network connectivity.

The Zen4 system is architected from the ground up to exploit a tight coupling between the network data plane and the application computing plane.

Fabric Computing

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Fabric Computing

Fabric computing is the logical extension of the existing concept of a VLAN to include servers and services. Zen4 system enables the convergence of the network and application networking environment. Fabric computing is the mechanism for achieving this integration.

Tech Company Systems offers the system administrator the opportunity to unify network and server management. Typically four different devices are used to implement the network, servers, storage, and application services. The Zen4 system unifies these four components into one server. The Tech Company Zen4 system management infrastructure manages VLANs as a transparent extension of a management fabric.

Functional Overview and Features

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Functional Overview and Features

The Zen4 system is a fabric server that integrates the following data processing and I/O capabilities:

- Partitionable N-socket symmetric multiprocessing (SMP) with large memory using industry-standard x86-64 microprocessors and Linux® operating systems
- Over 30 Gbps Ethernet network and Fibre Channel I/O bandwidth
- Application services such as server load balancing, and Secure Socket Layer (SSL)

The Zen4 system, built around an innovative terabit-class fabric, uses proprietary virtualization techniques. The servers combine partitionable SMP complexes with high-performance networking and storage interfaces to deliver world-class performance. Volume components (64 bit x86 architecture) and off-the-shelf operating systems provide binary compatibility for existing applications. Zen4 hardware resources combine to provide an enterprise server with the following features:

- **Performance** for network-intensive applications through the tight coupling of network line cards and processor complexes
- **Scalability** through the modular multi-chassis architecture
- **Manageability** through the consolidation of server and network resources, simplified provisioning and management, virtualized server capabilities, and location-independent server deployment
- **Resiliency** for enterprise applications through server partitioning and integrated load-balancing
- **Interoperability** with existing application infrastructure through support of standards like TCP/IP, 1-Gbps/10-Gbps Ethernet, 2-Gbps Fibre Channel, and SNMP

Integrated Computing and Networking

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Integrated Computing and Networking

The Zen4 system can be deployed to deliver enterprise applications and services on demand from resources within a single chassis, across multiple chassis in one location, or over geographically dispersed sites. The Zen4 system is also integrated with an industry standard Ethernet switch fabric to seamlessly integrate state-of-the-art computing resources with high-speed networking and I/O.

Resource Sharing Across Switch Fabric

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Resource Sharing Across Switch Fabric

The Zen4 system combines eight-socket partitionable SMP using 64-bit AMD Opteron® processors with 1-Gbps/10-Gbps Ethernet networking, 2-Gbps Fibre Channel storage I/O, and offloaded application or acceleration services. Hardware-based partitioning and virtualization enable pooling and sharing of resources ().

Figure 1-1. Multi-chassis Fabric with Resource Sharing

The network and storage I/O can be dynamically allocated across a built-in 80-Gbps switch fabric. Fabric-wide Quality of Service (QoS) ensures application service levels in a shared environment. Multiple Zen4 chassis can be directly coupled and managed as a single pool of resources.

The highly integrated fabric server collapses multiple computing and network infrastructure tiers and enables fabric computing across multiple sites. Policy based, fabric-wide management software allows rapid deployment, provisioning, and scaling of resources from any point on the fabric. The result is a mainframe-class architecture that offers high throughput and high stability for Linux and Windows applications.

Switch

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Switch

The Zen4 system includes a built-in switch. This switch behaves and can be configured just like any state-of-the-art Layer 2 switch. It supports virtual LANs (VLANs) and the set of Layer 2 protocols.

The switch supports physical and logical ports. Logical ports are used to create Layer 2 connections to virtual network interface controllers (VNICs) within the system. Logical ports can also be used to create Layer 3 ports on a VLAN to allow IP routing to and from the VLAN. Logical ports are managed in exactly the same way that physical ports are managed.

Any port on the switch, logical or physical, can be configured to behave as a Layer 2 port. As a result of the IP address assignment, an underlying MAC address will also be assigned, allowing this IP assignment to be addressed and packets to be sent to it. This IP address is generally called a “gateway” IP address.

Network Interfaces

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Network Interfaces

Network interfaces provide the means for external networks to be connected to the node by providing the interface between the external network and the internal IO fabric. A network interface provides all of the functionality of a typical enterprise switch, including classification, queuing, routing, policing, traffic shaping, etc. Network interfaces are provided currently for Ethernet (1-Gbs and 10-Gbs) and 2-Gbps Fibre Channel.

Ethernet network interfaces are deployed on modules called Ethernet Network Modules (ENMs). The ENMs contain the MACs and PHYs for the particular media, NPUs, traffic managers, support processors, and a fabric interface.

Fibre channel interfaces are deployed on modules called Fibre Channel Modules (FCMs). FCMs contain the MACs and PHYs for the Fibre Channel media, support processors, and a fabric interface.

Virtual I/O Interfaces

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Virtual I/O Interfaces

Tech Company virtual I/O interfaces conform to the following principles:

- A fabric server is built from a partition consisting of a processor and memory complex to which virtual I/O interfaces are added.
- There are three types of virtual I/O interfaces:
 - VNICs, which present Ethernet interfaces to the servers within the context of VLANs.
 - iSCSI initiators, which offload the iSCSI protocol to hardware within the context of storage VLANs.
 - Virtual service interfaces (VSIs), which provide data network connectivity to Application Services Modules (ASMs)
- All virtual I/O interfaces offer independent bandwidth control and three available classes of service (managed as priorities): low, medium, and high.

Flexible Provisioning

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Flexible Provisioning

The Tech Company Zen4 unified fabric management architecture merges the network control plane with server provisioning and management, bringing simplicity, agility, and cost-efficiency to the operation of the servers.

Technical Overview

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Technical Overview

The Zen4 system is a collection of resources arranged around a coherent fabric and a network or I/O fabric. Three broad types of resources are attached to the fabrics and linked through an internal switch: processing and memory, I/O modules (Ethernet and Fibre Channel), and application off-load or acceleration services. The Z-Series System Module (ZSM) monitors and manages these resources. The processors and associated memory are organized as standard SMP servers, allowing flexible combining and partitioning to meet application needs. The Ethernet and Fibre Channel interfaces provide connections to the external network and to storage resources. The Zen4 system includes built-in Layer 2 network switching capabilities.

Within a Zen4 system are multiple operating environments, including user operating environments for customer application deployment and internal operating environments for the Zen4 software. The user operating system (for example, SUSE® Linux Enterprise Server 9 SP2) runs in a partition to create a server that runs user applications.

Reliability, availability, and serviceability (RAS) are three qualities that represent the collective quality-of-service attributes of network systems. The Zen4 system has a combination of features, hardware design, and software design that maximizes uptime and minimizes downtime. Hardware design features that contribute to high levels of RAS include front access to most components for servicing, redundant cooling and power systems, and redundancy of system control modules and network interfaces. A graphical user interface (GUI) and command line interface (CLI) are available for managing system resources; in addition, an SNMP agent allows the Zen4 chassis to be integrated into enterprise monitoring systems such as HP OpenView or IBM Tivoli® for diagnostics, monitoring, and troubleshooting. The partition boot architecture of the Zen4 system helps minimize downtime arising from disruptive operating system updates.

Server administration and network administration are combined in the Zen4 system; the flexible security model provided by the Zen4 platform allows these functions to be separated in settings where this is preferred. The Zen4 platform provides fine-grained security and role-based access control that defines specific access privileges for different user roles. In addition to

the default user roles, you can also define other specific roles and access privileges.

Figure 1-2 shows a block diagram of the Zen4 system.

Figure 1-1. Zen4 System Block Diagram

Processors, Memory, and Partitioning

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Processors, Memory, and Partitioning

Application processors are deployed on modules called Processor and Memory Modules (PMMs). PMMs support general-purpose computing requirements and are available in two series: PMM-0410s and PMM-0200s.

- PMM-0410s provide processor sockets for up to four AMD Opteron 64-bit x86 CPUs with memory. The PMM-0410 also offers a total of 8 Gbps of storage I/O bandwidth using Fibre Channel interfaces.
- PMM-0200s provide CPU sockets for a maximum of two AMD Opteron 64-bit x86 CPUs with memory. Applications can be installed on a PMM-0200 to provide low-latency access by the PMM-0410. Such a configuration can improve performance for certain applications on the PMM-0410 that depend on other applications that can be accessed with low latency.

The application processors and memory are the only resources that attach to the coherency fabric. The processors and memory on a PMM can be organized into standard SMP servers; in a chassis equipped with PMM-0410s, multiple PMM-0410s can be linked through the coherency fabric (backplane) to create instances of SMP servers containing up to eight processor sockets. Smaller partitions of two or four processors can also be configured.

A chassis equipped with two PMM-0410s can support eight system processors (8 cores with single-core processors or 16 cores with dual-core processors), 128 GB of system memory, 30 Gbps allocated between network traffic and storage traffic, and three Application Service Modules (ASMs).

The PMM-0410s and coherency fabric support physical partitioning of the processors and memory. Because each partition is an independent server, multiple independent instances of operating systems can be hosted concurrently. A partition can be created, initialized, started, stopped, reset, or destroyed without affecting the operation of other partitions. Each partition appears as a separate entity for system management.

Physical partitioning is implemented in the hardware and in system software. The hardware ensures that hardware and software faults in one hardware partition cannot propagate to another partition.

System Management

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

System Management

System management is implemented through a combination of management software components and a distributed hardware management subsystem. Through the hardware management subsystem, system components communicate with the ZSM, which manages chassis resources. The hardware management subsystem also allows remote, “lights-out” operation of the Zen4 system. This management capability extends to a system in the standby power state, when it has limited operational capabilities as it waits for instructions. All system messages are directed to the ZSM console and system log (syslog) facility.

Access to the Zen4 system for management and software installation is through network or serial connections, eliminating the need for keyboard, video, and monitor connectors on the system itself. In addition, because all necessary software installation can be accomplished through a network connection, the Zen4 system is designed without a CD-ROM drive.

The Zen4 chassis has an LCD front panel display with associated selection buttons. Using the front panel display, you can view system status information and restart the chassis. The CLI, accessible through a direct console port connection or a network connection, provides complete management functions for the system. The Tech Company Z-Visor™ software provides the same management capabilities as the CLI, through a user-friendly graphical interface. Z-Visor also provides visual alarms and alerts.

System I/O Fabric

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

System I/O Fabric

All system modules are tied together through an I/O fabric implemented as a 32 x 32 crossbar switch. The system has 11 network fabric ports, allocated as follows:

- Two 10-Gbps ports are assigned to each of two PMM-0410s (up to four ports total).
- One 10-Gbps port is assigned to each I/O module installed in slot 5, 6, or 7 of the Zen4 chassis (support for up to three ENMs or up to two FCMs, providing up to three or two ports total).
- One 2.5-Gbps port is assigned to each ASM or PMM-0200 installed in slots 8, 9, and 10 of the Zen4 chassis (up to three ports total).
- One 2.5-Gbps port is assigned to the ZSM.

The switch hardware is instantiated on the ZSM.

ENMs are available with fixed 1-Gbps copper Ethernet ports, 1-Gbps SFP Ethernet ports, or 10-Gbps optical Ethernet ports. The ENMs provide an interface between the external network and the internal I/O fabric. Up to three ENMs can be installed in the Zen4 chassis, for a total network bandwidth of 30 Gbps.

FCMs are available with eight 2-Gbps Fibre Channel interfaces. One FCM provides access to an aggregate of 16-Gbps Fibre Channel I/O bandwidth through 2-Gbps Fibre Channel interfaces. A system with two installed FCMs, therefore, provides a total of 32 Gbps of Fibre Channel I/O. In addition, each PMM-0410 has dedicated Fibre Channel ports that are associated only with the server partitions on that PMM.

The fabric supports four priorities for general traffic. The use of the priorities is determined by software through configuration of the hardware, with the exception that all I/O control protocol read response messages are fixed to use fabric priority 0.

Boot Support

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Boot Support

Traditional servers include local (built-in) or direct-attach disks to store an operating system that they boot from. This model imposes severe operational constraints that reduce flexibility in usage and prevent easy redeployment of computing resources. The Zen4 system model is based on an abstract server definition that is not locked into a chassis. A server can be instantiated using resources available anywhere on the fabric and with resources contributed by multiple chassis. The operating system itself is a resource on the fabric, located on a network element or on a Fibre Channel storage array.

In this distributed model of a server, booting can occur in the following ways:

- Using the PXE mechanism, from a boot server in the network
- Using Fibre Channel:
 - From a storage area network (SAN) with the operating system installed on a logical unit number (LUN) on a Fibre Channel storage array that is connected to a SAN switch through a PMM
 - From a direct-attached Fibre Channel storage array with the operating system installed on a LUN in the array that is attached directly to a Fibre Channel port on a Zen4 system
- Using iSCSI from an external storage target connected to an FCM in a Zen4 system
- Using iSCSI from an external iSCSI storage target connected to an ENM in a Zen4 system

Backplane

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Backplane

The Zen4 backplane is designed to allow system growth. Each slot is provided with connectors to support twice the bandwidth necessary for the initial system. By changing the ZSM, a system can be upgraded to twice the traffic on the backplane. The backplane carries two major fabrics, the system IO fabric and the processor coherency fabric.

Internal Hard Drive

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Internal Hard Drive

The Zen4 system is designed to provide “diskless operation” and therefore does not include an internal hard drive for the user operating system (UOS). The Zen4 provisioning facility allows users to create flexible server configurations that can be revised and reconfigured quickly based on a number of considerations. This flexibility is lost if the operating system resides on an internal hard drive. An optional direct-attached external hard drive subsystem is available for supporting traditional boot configurations.

Long-term storage for the management application is provided by an on-board flash disk and a 2.5-inch hard disk on the ZSM. The flash disk is used for Zen4 operating system boot, configuration data, and application software. The 2.5-inch hard disk is used for logging.

System Battery/System Time

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

System Battery/System Time

Over time, batteries can leak and damage other system components. To increase system reliability, the ZSM uses a capacitor, rather than a battery, to maintain the system time when the chassis is not plugged into a power source. The system time can be maintained for approximately 48 hours while the chassis is unplugged.

Software Components

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Software Components

Software components of the Zen4 system include the system software image, user operating system, and management software that includes a command line interface (CLI) and the Z-Visor software graphical user interface (GUI).

The system software image resides on the ZSM; it manages the chassis hardware resources, including the server partitions. User operating systems are associated with partitions and execute on the processors on the PMM. The command line interface is accessible through a console connection or from a client workstation. Z-Visor software is accessed from a management workstation and manages the Zen4 system through an Ethernet connection to the ZSM.

Typical System Installation

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Typical System Installation

Figure 1-3 shows a typical installation of the Zen4 system with four server partitions. Each partition has two Fibre Channel I/O connections to a storage area network (SAN) and two Ethernet connections to the external network. The ZSM has an Ethernet connection and a serial connection to a management network.

Zen4 Hardware Overview

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Zen4 Hardware Overview

The Zen4 system consists of a 21U rack-mount chassis with the following installed resources:

- **Processor and Memory Modules (PMMs)** support general-purpose computing requirements and come in two series: PMM-0410s and PMM-0200s.
 - **PMM-0410:** PMM-0410s provide CPU sockets for up to four AMD Opteron 64-bit x86 CPUs with memory. The PMM-0410 also offers a total of 8 Gbps of storage I/O bandwidth using hard-wired Fibre Channel interfaces. PMM-0410s are installed in Zen4 chassis slots 1 and 2.
 - **PMM-0200:** PMM-0200s provide CPU sockets for a maximum of two AMD Opteron 64-bit x86 CPUs with memory. The PMM-0200 augments the CPU and memory resources already available through the two PMM-0410s. Each PMM-0200 represents an extra, isolated, two-socket server partition that can host certain proximal distributed application components that might be effectively off-loaded from the PMM-0410s. PMM-0200s are installed in chassis slots 8, 9, or 10.
- **Q-Series System Modules (ZSMs)** that implement provisioning, system management, and fabric management capabilities. The ZSM is installed in chassis slot 4.
- **Ethernet Network Modules (ENMs)**, each providing an aggregate of 10 Gbps of network I/O bandwidth, using either copper or fiber optic interfaces. Up to three ENMs can be installed in chassis slots 5, 6, and 7. (These slots can be used for either ENMs or FCMs.)
- **Fibre Channel Modules (FCMs)** that interface to storage arrays and storage devices, either directly or indirectly through storage area networks (SANs). An FCM can be installed in chassis slot 5, 6, or 7. (These slots can be used for either ENMs or FCMs.)
- **Application Service Modules (ASMs)** that provide acceleration facilities for specialized functions such as load balancing, encryption, and XML processing. Up to three ASMs can be installed in chassis slots 8, 9, and 10.

Multiple chassis can be interconnected to operate in a network fabric where physical resources in one chassis are available as virtualized resources and services anywhere on the fabric.

Processor and Memory Zen4 Subsystems Modules

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Processor and Memory Zen4 Subsystems Module

Zen4 PMMS use AMD Opteron 800 series processors. Four processors are available on each available on each PMM-0410; two processors are available on each PMM-0200. HyperTransport[™] links between the processors in a PMM and between two PMM-0410s allow all eight processors to be configured into a single symmetric multiprocessing (SMP) server. Smaller partitions of two or four processors can also be configured.

Z-Series System Module (ZSM)

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Z-Series System Module (ZSM)

The Z-Series System Module (ZSM) is the heart of the system. The ZSM manages the resources, monitors the health of all the components, and takes appropriate actions, in case of any failures, to maintain the system stability. The module is designed to be replicated in the system so that a failure on one module can instigate a failover to the other module. In general, a failure in any one subsystem on the module that causes that subsystem to failover will cause all subsystems to failover. This allows the failed module to be removed from the system for replacement.

Long-term storage for the management application is provided by an on-board flash disk and a 2.5-inch hard disk. The flash disk is used for OS boot, configuration data, and application software. The 2.5-inch hard disk is used for event logging. Software is responsible for maintaining a valid replica of critical data structures on the flash disk on the standby ZSM so that it is prepared to take over in the event of a failure. The storage devices on the ZSM are not customer-replaceable units.

The system clock on the ZSM provides system time-of-day.

Ethernet Network Module

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Ethernet Network Module

The Ethernet Network Module (ENM) provides an interface between the external network and the internal I/O fabric. ENMs have either optical or copper ports that provide up to 10 Gbps of aggregate network I/O bandwidth. Up to three ENMs can be installed in the Zen4 chassis, for a total network bandwidth of 30 Gbps.

Three versions of the ENM are available:

- The model ENM-1011 has ten 1-Gigabit copper (RJ-45) ports.
- The model ENM-1012 has ten 1-Gigabit small form-factor pluggable ports (SFPs).
- The model ENM-1103 has one 10-Gigabit optical port implemented as an installed XENPAK optical transceiver.
- The model ENM-2411 has 24 1-Gigabit copper (RJ-45) ports.

Any ENM type can be installed in one of the chassis slots 5, 6, or 7. The Zen4 system detects the installed module.

Fibre Channel Modules

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Fibre Channel Modules

Fibre Channel Modules (FCMs) interface to storage arrays and other storage devices, either directly or indirectly through Fibre Channel switches in storage area networks (SANs). Up to two FCMs can be installed in chassis slots 5, 6, or 7.

Application Service Module

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Application Service Module

Application Service Modules (ASMs) provide hardware acceleration facilities for specialized functions such as load balancing, Secure Socket Layer (SSL), and XML processing. ASMs are installed in chassis slots 8, 9, or 10.

Hot-Plugged and Controlled Hot Removal Capability

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Hot-Plugged and Controlled Hot Removal Capability

All the modules used in the Zen4 system have circuitry to allow removal and insertion of a module without interrupting system power. This is accomplished by controlling the inrush current and power sequencing on the boards.

High Availability

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

High Availability

The system is designed with redundant subsystems to ensure high availability of resources. Four power modules that can be connected to two independent power feeds share the power load during normal operation. If one power feed fails, the remaining two power modules can provide sufficient power for the system. Two fan trays, each with six fans, provide cooling for the chassis. If one tray (or part of a tray) fails, the ZSM increases the speed of the remaining fans to maintain cooling until the faulty fan tray can be replaced. Multiple interfaces are available on the and ENMs to provide redundancy for storage and network access.

Virtual I/O Controller (VIOC) and Virtualization Capabilities

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Virtual I/O Controller (VIOC) and Virtualization Capabilities

Each PMM is assigned a virtual I/O interface with appropriate properties that depend on whether it is used for network, storage or services. A virtual I/O interface is called a virtual NIC (VNIC) when it is used for network data, or a VNIC used as iSCSI initiator when it is used for storage data. A virtual I/O storage interface is called a virtual service interface (VSI) when it is used in an ASM.

Each PMM-0410 has two VIOCs, and each PMM-0200 has one VIOC. In addition, each ASM and FCM has one VIOC. The VIOC implements the virtual NICs (VNICs) and iSCSI initiators that allow a server to communicate across the fabric with other servers within a complex, or with any server outside a complex. Through the VIOC, the management subsystem creates and manipulates these virtual interfaces. Virtual I/O interfaces support three types of traffic: network, storage, and application services.

Each VIOC supports up to 16 virtual interfaces; you provision the number of interfaces you need.

shows a logical view of the system as it will be seen by the system administrator or network administrator. VNICs are at the left side of the diagram. In the center is the Zen4 system, represented as a single large device, and at the right are the physical media ports that connect to the external network. Layered behind the picture are boxes representing the hardware components that implement the various logical functions. The VNICs and a portion of the switch/router are shown as being implemented on one or more PMMs. The physical media ports and a portion of the switch are shown as being resident on one or more ENMs. The implementation of the rest of the switch is distributed across the fabric, route processor, VIOC, and ENMs. The Zen4 server is a multilevel server/switch capable of operating in Layer-2-only mode.

Virtual Network Interface Controllers

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Virtual Network Interface Controllers

Virtual network interface controllers (VNICs) represent end-points on the Layer 2 network and therefore are always assigned a Layer 2 MAC address. A user operating system (UOS) connects to the switching and routing fabric within the Zen4 system through the VNICs. The VNIC communicates with the address space of the operating system instance to which it has been assigned, or by which it is owned. Each VNIC on a given VIOC could be owned by a different UOS instance, or several of them could be owned by the same UOS instance.

Each VNIC can be logically connected to a logical Layer-2-only port on the switch/router, as shown in .

The total bandwidth available through one VIOC is 10 Gbps, allocated to the VNICs managed by the VIOC. The bandwidth allocation is managed by VNIC rate-limiting that is implemented using a token bucket scheme. For information about configuring the VNIC bandwidth allocation, see .

Virtual Storage Interfaces

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Virtual Storage Interfaces

The initial virtual storage interface implementation (Zen4 Release 1.1) is as an iSCSI initiator. The iSCSI initiator interfaces to a virtual iSCSI target (typically on a storage VLAN) on the Fibre Channel Module (FCM). The iSCSI target connects to a Fibre Channel port on the FCM. The FCM Fibre Channel port is, in turn, cabled to a Fibre Channel switch or storage array.

The FCM serves as a gateway between the virtual iSCSI target and the Fibre Channel port on the FCM.

Each virtual storage interface has a nexus—a storage connection on a server, specifying the end-to-end path to the storage device. The nexus includes the virtual initiator, a virtual target interface, the world wide port name (WWPN), and the logical unit number (LUN) corresponding to the target. The nexus facility provides LUN masking and access control.

Partitioning and Virtualizing Resources

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Partitioning and Virtualizing Resources

Tech Company systems leverage the technology of virtualizable resources, to allow you to flexibly partition the system to match data center needs. Network interfaces, application processors, and the fabric itself can be partitioned to match the resource requirements of an application. For example, a traditional multi-tiered web-based application, as it might be deployed with traditional fixed-size boxes, requires a collection of various sized servers, routers, and appliances. As the workload expands, additional devices of the appropriate type are brought in, cabled appropriately, and deployed. As the workload shrinks, servers and routers could be uncabled and moved to a new location to be reused.

The same application can be mapped to a Zen4 system as shown in . Here the node is logically partitioned to provide the computing, network, and fabric resources demanded by the application. As the workload expands, additional partitions can be created and logically added to the application without physically moving boxes or plugging cables. As the workload shrinks, resources can be removed to be logically redeployed elsewhere, again without physically touching the boxes or the network.

Figure 1-1. Zen4 System Deployment in an Enterprise Data Center

If an application expands beyond the size of a single node, additional nodes can be added to the system. The system is still managed as a single entity, and resources from multiple nodes can be combined for a given distributed application.

shows a possible functional organization of one of the Zen4 chassis in the deployment shown in .

Figure 1-2. Possible Functional Organization of a Single Zen4 System

Data Flow in the Zen4 System

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Data Flow in the Zen4 System

This section outlines the communication paths between different modules in the Zen4 chassis. The modules send and receive data traffic over these paths connected through the switch fabric. Control traffic goes over a separate management network in the system.

The following communication paths are shown in :

1. PMM to/from PMM.
2. PMM to/from PMM (through switch fabric, IPC traffic using F7 Messaging Protocol).
3. Ethernet to/from Ethernet. (System acts like a bridge/router for this transit traffic.)
4. Ethernet to/from PMM (TCP traffic and F7MP).
5. Ethernet to/from Route Processor (through switch fabric).
6. PMM to/from local Fibre Channel ports.
7. PMM to/from route processor.
8. PMM to/from Fibre Channel Module

Figure 1-1. Data Flow in the Zen4 Server

Appendix A Product Support

This appendix provides information about product warranties, customer service, returning components, and ordering replacement or spare components.

Note: For additional product support information that is not covered in this appendix, visit the Tech Company Customer Support web site or call one of the customer service phone numbers listed in table A-1.

Warranty

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Warranty

Zen4 systems are covered by a comprehensive warranty. For detailed information about the standard warranty, contact the Tech Company Sales or Customer Support Team.

Verify Warranty Status

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Verify Warranty Status

How to Verify Warranty Status

To verify warranty status, contact Tech Company Customer Support or your Tech Company account representative.

You will need the chassis serial number from the label on the back of the Zen4 chassis.

Service Features and Levels

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Service Features and Levels

The goal of the Tech Company Customer Support organization is to consistently deliver the quality of service you require in a mission-critical, data center environment. Tech Company is committed to providing around-the-clock customer service, either directly or through our service partners who have been factory-trained and certified by Tech Company Systems. You can log calls at any time by telephone or email, or through a web interface to our support system. All calls are actively managed to conclusion by a Tech Company Support Engineer. (A service partner may provide the on-site repair services.) Status tracking is available via the web interface to our support system.

Tech Company provides multiple scalable service levels to suit individual customer needs. Some of the service levels include access to an assigned Tech Company Customer Support account engineer. This engineer can help you with installation and upgrade planning and provide progress reviews. An assigned account engineer is the primary point of contact for handling service calls.

Customers with the appropriate service contract may designate one of the following priority levels for service calls:

- Priority 1, highest severity; work starts immediately to resolve the problem.
- Priority 2, medium severity; work starts within 1 hour to resolve the problem.
- Priority 3, lowest severity; work starts within 4 hours to resolve the problem.

Contacting Customer Support

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Contacting Customer Support

For additional information about customer service, visit the Tech Company web site at:
To contact Customer Support, use the phone numbers or email address in .

Table 1-1. Contacting Tech Company Customer Support

USA		
24-hour hotline	1-800-968-6501	Email: support@Tech Company.com

Return Materials Authorization (RMA) Procedure

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Return Materials Authorization (RMA) Procedure

Tech Company systems are covered by a 1-year comprehensive on-site warranty covering parts and labor. Following the warranty period, systems will normally be maintained by Tech Company under the terms of a service agreement covering parts and labor. For customers who wish to maintain their own systems and obtain replacement parts from Tech Company, we offer a parts replacement service which includes this RMA procedure.

Tech Company will, at its option, repair or replace any product or component that fails during the term of the parts replacement service agreement at no cost to you, provided that you contact the Tech Company Support Center to report the failure and that you comply with the Tech Company return policies.

A replacement product or component will be shipped to you on the first contracted day following confirmation of the failure. When you receive the replacement, you must return the failed product or component to Tech Company under the RMA number issued by Tech Company. Tech Company may invoice for any failed products or components under the following two conditions:

- You have caused further damage to the product or component.
- The product or component is not returned within 10 days of receipt of the replacement.

Return a Product or Component

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Return a Product or Component

Labeling Requirements for Return Packages

Products returned to Tech Company must be pre-authorized by Tech Company with an RMA number marked on the outside of the package, and sent prepaid, insured, and packaged appropriately for safe shipment using the packaging that the replacement was sent in. Only packages with RMA numbers written on the outside of the shipping carton and/or the packing slips and shipping paperwork will be accepted by the Tech Company receiving department. All other packages will be rejected.

Steps to Return a Product or Component

To return a component:

1. **Contact the Tech Company Customer Support Center Hotline to request a replacement component.**
 - Be prepared to provide the following information:
 - Chassis serial number
 - Serial number of item to be returned
 - Model number of item to be returned
 - Description of problem
 - Return address and phone number

Tech Company will issue an RMA number and ship a replacement component.
2. **After the replacement item has been unpacked and installed, use the same packaging materials to pack the defective item for return to Tech Company.**
3. **Make sure that the RMA number is clearly marked on the packaging exterior.**
4. **Ship the product back to Tech Company using the carrier designated by Tech Company.**

Result

Title to any returned products or components will transfer to Tech Company upon receipt. Tech Company will be responsible for all freight charges for returned products or components as long as you use the carrier designated by Tech Company.

Ordering Replacement Parts or Spares

Abstract

[Abstract element: Author will need to write introductory content that would be unfit for a short description element.]

Ordering Replacement Parts or Spares

To order replacement parts or spares, visit the Tech Company Customer Support web site or contact your Tech Company account representative.

Glossary

M

My Term

My definition

Index

A

abstract server definition 24

advanced data center computing 8

AMD Opteron 13

appliances 42

application processors 20, 42

Application Service Module 30, 36

Application Services Modules 16

application software 26

Architectural Overview 8

architecture 11, 13

ASM 23, 30, 36

ASMs 16

B

Backplane 25

bandwidth 25

bandwidth 40

batteries 27

Boot Support 24

booting 24

C

cables 42

capacitor 27

chassis 11-13, 22, 24, 27-28, 31, 36, 46, 50

CLI commands 18

clI commands 22

Command Line interface (CLI) 28

communication paths 43

configuration data 26

Control traffic 43

copper port 34

customer service 44, 47-48

customer support 44-49, 52

D

Data Flow 8, 43

data processing 11

data traffic 43

diskless operation 26

display, front panel 22

distributed application 42

E

ENM 24, 30, 34, 38

ENMs 15, 23

enterprise applications 12

enterprise server 11

enterprise switch 15

Ethernet 11-13, 15, 43

ethernet 18

Ethernet connection 29

Ethernet interfaces 16

Ethernet network interfaces 15

Ethernet Network Module 30, 34

Ethernet Network Modules 15

Ethernet ports 23

external network 15

external networks 15

external storage target 24

F

F7 Messaging Protocol 43

F7MP 43

fabric 18, 20, 24, 42

fabric computing 13

fabric interface 15

fabric port 23

fabric server 11, 13, 16

fabrics 25

fan tray 38

FCM 24, 30, 35

FCMs 15, 23

Fiber Channel Module 41

Fibre Channel 11, 15, 18, 24

Fibre Channel I/O 29

Fibre Channel I/O bandwidth 11

Fibre Channel Module 30, 41

Fibre Channel Modules 15, 35

Fibre Channel port 41

Fibre Channel ports 23, 43

Fibre Channel storage I/O 13

flash disk 33

flexible security 18

front panel display 22

G

gateway 14

graphic user interface (GUI) 28

GUI 18

H

hard disk 26

hardware management subsystem 22

Hardware Overview 8

Hot Removal 37

Hot-Plugged 37

HypertTransport links 32

I

I/O 12, 18

I/O capabilities 11

I/O fabric 23

I/O module 23

I/O modules 18

I/O, storage 23

independent bandwidth control 16

independent power feeds 38

initial virtual storage interface 41

inrush current 37

Integrated Computing 12

interface 15

Internal Hard Drive 26

internal hard drive 26

internal I/O fabric 34

internal IO fabric 15

IP assignment 14

IP routing 14

IPC traffic 43

iSCSI 24

iSCSI initiator 41

iSCSI initiators 16, 39

iSCSI protocol 16

iSCSI target 41

L

Layer 2 connections 14

Layer 2 network connectivity 9, 18

Layer 2 protocols 14

Layer 2 switch 14

Layer 3 ports 14

Linux 11

logic unit number 41

logical ports 14

logical unit number 24

LUN 24

LUN masking 41

M

MAC address 14, 40

MACs 15

microprocessors 11

model number 50

modular design 9

modules 43

multiprocessing 9

N

network bandwidth 34

network control plane 17

Network Interfaces 15

Network interfaces 42

network line cards 11

networking 9, 12

Networking 12

nexus 41

node 15, 42

NPUs 15

N-socket symmetric multiprocessing 11

O

on-board flash disk 26

Opteron 800 series processor 32

optical port 34

overview, system 13

P

partition 16, 20

partitionable 13

Partitioning 8, 18, 42

partitioning 11, 20-21

PHYs 15

physical partitioning 20

physical ports 14

PMM 20, 24, 39, 43

PMM partition 20

PMM-0200 20, 23

PMMS 32

processor and memory complex 16

Processor and Memory Module 20

Processor and Memory Module. See PMM-0410 or PMM-0200 30

processor coherency fabric 25

processor complexes 11

processors 13

- application 20

product support 44

PXE mechanism 24

Q

QoS 13

Q-Series System Modules 30

Quality of Service 13

R

RAS 18

redundant subsystems 38

reliability, availability, and serviceability (RAS) 18

replacements, ordering 44, 49, 52

resource types 18

return Materials Authorization. See RMA procedure 49

Return Materials Authorization. See RMA procedure 50

RMA number 49-50

RMA procedure 49

role-based security 18

Route Processor 43

routers 42

S

SAN 24

Secure Socket Layer. See SSL. 36

security 18

security, flexible 18

serial number 50

server 24

server deployment 11

server partitions 29

server provisioning and management 17

servers 9, 17-18, 20, 42

service levels 47

small form-factor pluggable ports. See SFP 34

SMP 11, 13, 18, 20, 32

SNMP 11

snMP 18

Software components 28

storage 26

storage area network 24, 29

storage area networks 35

storage I/O 20, 23

storage VLANs 16

Switch 14

switch 18

switch fabri 43

switch fabric 12, 43

system growth 25

System I/O Fabric 23

system IO fabric 25

system overview 13

system reliability 27

system time 27

T

TCP traffic 43

TCP/IP 11

Tech Company web site 48

Tech Company Zen4 System 8

Technical Overview 8

Typical System Installation 8

Typical system Installation 29

U

unified fabric management architecture 17

UOS 26, 40

user operating system 26, 40

V

VIOC 8, 39-40

Virtual I/O Controller 8

virtual I/O interface 39

Virtual I/O Interfaces 16, 39

virtual LANs 14

virtual network interface controllers 14

Virtual network interface controllers 40

virtual NIC 39

virtual service interface 39

Virtual service interfaces 16

virtualizable resources 42

Virtualization 8

virtualization 11, 13

virtualized server capabilities 11

Virtualizing 8, 42

Vista management software 22

VLANs 14, 16

VNIC 39-40

VNICs 14, 16, 39

VSI 39

VSIs 16

W

warranty 45-46, 49

world wide port name 41

Z

Zen4 29-30, 37

zen4 chassis 18

Zen4 chassis 42, 46

Zen4 Hardware Overview 8, 30

Zen4 server 8

Zen4 System 8

Zen4 system 9, 14, 18, 45

Z-Series System Module 33

ZSM 23, 25-27, 30, 33, 38

ZSM (Z-Series System Module) 18, 22

Z-Visor management software 22